

DIGITAL LUX METER

Cost effective pocket size lux meter which measures lux intensity both in terms of Foot candle (Fc) or lux (lx). Has the feature of low battery indication and peak hold.



Features

- 4 3½ digital LCD display
- 4 Max Hold and Data Hold
- 4 Auto Power Off
- 4 Low battery indication
- 4 User selectable Fc/Lux

Specifications

| | |
|---------------------|---------------------------------|
| Display | LCD 1999 Counts |
| Measuring Range | 0 to 50,000 lux |
| Accuracy | ±5% + 10d (< 10,000 lux) |
| Repeatability | ± 2% |
| Measuring Range | 1.5 times / sec |
| Auto Power off | After 15 min. of Inactivity |
| Photo Detector | Silicon photo diode with filter |
| Dimension | 188 × 64.5 × 24.5 (H × W × D) |
| Storage Temperature | -10 to 60°C at < 80% RH |
| Power Supply | 1 × 1.2 V Battery |
| Weight | 160gms |

TECHNO INSTRUMENTS COMPANY

37,3rd Main Road, Vyalikaval, Bangalore-560 003. INDIA

Phone : 080-23349239 / 23449007. E-mail:tic_ci80@hotmail.com Web: www.technoinstruments.co.in